

	MANUAL				ECO		IN-GROUND		
	15M100 AZT	15M200 AZT	15M300 AZT	15M600 AZT	15E60 BK	15E120 BK	15IGT100	15IGT300	15IGT600
	8"x 3.25"x 3"	13.25"x 3.5"x 4"	13.5"x 4.5"x 4"	14.25"x 5.5"x 5"	6.75"x 3.75"x 3.75"	6.75"x 3.75"x 3.75"	9.625"x 13.25" dia.	9.625"x 13.25" dia.	9.625"x 13.25" dia.
Wattage (VA)	100	200	300	600	60	120	100	200	300
Automatic Timer					●	●	●	●	●
Photoelectric Eye					●	●	●	●	●
High-Low Switch					●	●			
On-Off-Auto Switch					●	●			
Multi-Tap Connection 12V, 13V, 15V			●	●					
Multi-Tap Connection 12V, 13V, 14V, 15V							●	●	●
Single-Tap Connection 15V									
Thermal Cut-Off on Primary Side	●	●	●	●	●	●	●	●	●
Thermal Reset Breaker on Secondary Side	●	●			●	●			
Magnetic Breaker on Secondary Side			●	●			●	●	●
Easy-Connect Terminal Blocks		●	●	●					
6', 3-Wire #14-GA SJTW Cord									
6', 3-Wire #16-3 SJTW Cord				●					
6', 3-Wire #18-3 SJTW Cord	●	●	●						
6', 2-Wire #18-2 SJTW Cord					●	●			
Includes Mounting Hardware									
Textured Architectural Bronze or Powder Coat Finish	●	●	●	●					
#304 Grade Stainless Steel									
Composite Housing					●	●	●	●	●
High-Efficiency E.I. Core and Coil Configuration	●	●	●	●	●	●			
High-Efficiency Toroid Core and Coil Configuration							●	●	●

For warranty information, visit [Kichler.com/Warranty](https://www.kichler.com/Warranty).

600W, 900W and 1200W Transformer models are manufactured in intervals of 300W (VA) circuits.

National Electric Code and Underwriters Laboratories require that wiring, where concealed or extended through a building wall, must be enclosed in conduit. All transformers are for use with outdoor low-voltage lighting.



All Kichler transformers are listed or certified to ANSI/UL 1838. The listing/certification agency may vary.